


# **TG 10000SSKV ECO**

PORTABLE LINE





## DIESEL ENGINE DRIVEN GENERATING SET 3000 r.p.m.









cooled



### TG 10000SSKV ECO

Code	PP14-10MS3	
DISTRIBUITION PANEL		
2x 16A-115V CEE socket		
1x 32A-115V CEE socket		
1x 32A-230V CEE socket		
1x 16A-230V CEE socket		
TECHNICAL DATA		
Single-phase power	10kVA - 230V	

CENEDATOR	
RPM	3000
Frequency	50 Hz
Power factor (cos φ)	0.8
Single-phase power	10kVA - 115V
Single-phase power	10kVA - 230V

#### GENERATOR LINIZ E1011M D

LINZEICTIMB	
Insulation Class	Н
Mechanical protection	IP23

Insulation Class	П
Mechanical protection	IP23
ENGINE	
Type	Kubota D722 *
EU Emission Stage	Stage 3
N. Cylinders	3
Displacement	719 cm <sup>3</sup>
Starting system	Electric
Cooling	Water
Fuel	Diesel
FUEL CONSUMPTION	
Fuel tank canacity	/ <sub>1</sub> 0 I

Fuel tank capacity	40 l
Fuel consumption 75% load PRP	2,8 l/h
Running time	14 h
DIMENSIONS & WEIGHT	

DIMENSIONS & WEIGHT	
Dry weight	350 Kg
Dimensions (L. x W. x H.)	1220 x 670 x 840 mm

<sup>\*</sup>Alternative Kohler equivalent engine should be fitted



Eco Auto Start/Stop mode allows the generator to automatically start & stop according to generator power demand

10kVA (230V / 110V) AC Aux Power

Linz alternator

Kubota electric start diesel engine (Stage 3)

HVO (Hydrotreated Vegetable Oil) fuel approved

Emergency stop button

Central lifting eye and front & side fork pockets

Fully bunded base (110%)

Complete with trolley kit + folding handles

## ON BOARD CONTROL PANEL EQUIPPED WITH:

Signal lamp for: Battery charger failure, Low oil pressure, High coolant temperature, Fuel reserve, Glow plug, Alarm,

Eco mode ON Hour counter

Key switch for: OFF/ECO MODE/MAN. START

Emergency stop

Volt meter

ELCB, Main protection

Fuel level monitor

Voltage selector: 115V/230V

## **NOISE LEVEL**

Noise level	89 Lwa
Acoustic pressure level 7m	64 dbA

The company reserves the right to modify the technical specifications, items and design without notice. The images of the products are indicative for illustrative purposes only.



